

ELECTRONIC FL BALLASTS

For 32W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F32T8 - 32W											
	1	120-277	Instant Start	7282	BAF232IS/MV	35-34	1.08	10	0.29-0.13	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	31-30	0.93	10	0.26-0.12	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	45	1.38	10	0.37-0.17	0/-18	-	844366072840
	2	120-277	Instant Start	7282	BAF232IS/MV	56-55	0.89	10	0.46-0.20	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	48-47	0.77	10	0.40-0.17	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	74-73	1.18	10	0.62-0.27	0/-18	-	844366072840
			Instant Start	7288	BAF332IS/MV	63	1.02	10	0.53-0.24	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	58-57	0.92	10	0.49-0.21	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	83-81	1.4	10	0.69-0.30	0/-18	-	844366072901
	3	120-277	Instant Start	7288	BAF332IS/MV	84-83	0.88	10	0.71-0.31	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	76-74	0.78	10	0.64-0.27	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	108-106	1.18	10	0.91-1.39	0/-18	-	844366072901
			Instant Start	7294	BAF432IS/MV	98-92	0.94	10	0.77-0.34	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	81-80	0.82	10	0.68-0.29	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	122-120	1.24	10	1.01-0.45	0/-18	-	844366072963
	4	120-277	Instant Start	7294	BAF432IS/MV	112-108	0.88	10	0.93-0.40	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	98-96	0.77	10	0.35-0.82	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	145-144	1.16	10	1.24-0.53	0/-18	-	844366072963

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

■ ■ ■ For 32W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F32T8 - 32W											
	2	120-277	Program Start	7300	BAF232PS/MV	57-56	0.88	10	0.48-0.21	0/-18	-	844366073007
			Program Start	7301	BAF232PS/MV/L	52-51	0.78	10	0.43-0.19	0/-18	-	844366073014
			Program Start	7302	BAF232PS/MV/H	72-71	1.18	10	0.60-0.26	0/-18	-	844366073021
	3	120-277	Program Start	7303	BAF332PS/MV	87-85	0.88	10	0.72-0.31	0/-18	-	844366073038
			Program Start	7304	BAF332PS/MV/H	113-110	1.18	10	0.95-0.42	0/-18	-	844366073045
	1	347	Instant Start	7305	BAF232IS/347	37	1.08	10	0.112	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	36	0.88	10	0.107	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	47	1.37	10	0.141	0/-18	-	844366073076
	2	347	Instant Start	7305	BAF232IS/347	56	0.89	10	0.17	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	51	0.83	10	0.151	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	74	1.18	10	0.222	0/-18	-	844366073076
			Instant Start	7308	BAF332IS/347	61	0.99	10	0.186	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	60	0.9	10	0.179	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	82	1.24	10	0.244	0/-18	-	844366073106
	3	347	Instant Start	7308	BAF332IS/347	81	0.86	10	0.24	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	75	0.78	10	0.225	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	107	1.15	10	0.324	0/-18	-	844366073106
			Instant Start	7311	BAF432IS/347	88	0.94	10	0.26	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	80	0.82	10	0.238	0/-18	-	844366073120
	4	347	Instant Start	7311	BAF432IS/347	108	0.87	10	0.32	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	98	0.77	10	0.296	0/-18	-	844366073120

ELECTRONIC FL BALLASTS

For 17W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F17T8 - 17W											
	1	120-277	Instant Start	7282	BAF232IS/MV	19	1.06	15	0.17-0.08	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	18	0.9	20	0.15-0.07	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	25	1.42	20	0.22-0.11	0/-18	-	844366072840
	2	120-277	Instant Start	7282	BAF232IS/MV	30	0.9	10	0.26-0.11	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	27	0.85	10	0.23-0.10	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	39	1.23	15	0.33-0.15	0/-18	-	844366072840
			Instant Start	7288	BAF332IS/MV	36	1.07	15	0.31-0.14	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	33	0.89	15	0.28-0.19	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	48	1.38	10	0.39-0.20	0/-18	-	844366072901
	3	120-277	Instant Start	7288	BAF332IS/MV	46	0.92	10	0.39-0.18	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	43	0.89	15	0.37-0.16	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	60-58	1.19	10	0.49-0.22	0/-18	-	844366072901
			Instant Start	7294	BAF432IS/MV	54-52	1.04	15	0.49-0.19	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	43	0.85	15	0.36-0.16	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	63	1.29	10	0.52-0.24	0/-18	-	844366072963

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

■ ■ ■ For 17W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F17T8 - 17W											
	4	120-277	Instant Start	7294	BAF432IS/MV	59	0.91	10	0.50-0.22	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	54-52	0.81	10	0.46-0.19	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	79-75	1.18	10	0.63-0.29	0/-18	-	844366072963
	2	347	Instant Start	7305	BAF232IS/347	33	0.91	10	0.101	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	32	0.88	10	0.094	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	43	1.22	10	0.128	0/-18	-	844366073076
	3	347	Instant Start	7308	BAF332IS/347	46	0.92	10	0.137	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	43	0.84	10	0.126	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	60	1.2	10	0.178	0/-18	-	844366073106
	4	347	Instant Start	7311	BAF432IS/347	60	0.91	10	0.176	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	55	0.79	10	0.162	0/-18	-	844366073120

ELECTRONIC FL BALLASTS

For 25W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F25T8 - 25W											
	1	120-277	Instant Start	7282	BAF232IS/MV	28	1.05	10	0.23-0.10	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	24	0.9	10	0.20-0.09	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	35	1.4	15	0.29-0.13	0/-18	-	844366072840
	2	120-277	Instant Start	7282	BAF232IS/MV	43	0.88	10	0.37-0.16	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	39	0.78	10	0.32-0.14	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	57	1.2	10	0.48-0.21	0/-18	-	844366072840
			Instant Start	7288	BAF332IS/MV	50	1.02	10	0.43-0.19	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	44	0.87	10	0.37-0.17	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	64	1.32	10	0.54-0.24	0/-18	-	844366072901
	3	120-277	Instant Start	7288	BAF332IS/MV	65	0.9	10	0.55-0.24	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	57	0.8	10	0.48-0.22	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	84	1.2	10	0.70-0.31	0/-18	-	844366072901
			Instant Start	7294	BAF432IS/MV	72	0.98	10	0.60-0.27	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	62-61	0.84	10	0.53-0.22	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	89-87	1.26	10	0.75-0.32	0/-18	-	844366072963

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

■ ■ ■ For 25W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F25T8 - 25W											
	4	120-277	Instant Start	7294	BAF432IS/MV	86	0.89	10	0.73-0.32	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	76-74	0.78	10	0.64-0.27	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	109	1.17	10	0.92-0.40	0/-18	-	844366072963
	2	120-277	Program Start	7300	BAF232PS/MV	50-49	1	10	0.42-0.18	0/-18	-	844366073007
			Program Start	7302	BAF232PS/MV/H	63-60	1.18	10	0.53-0.22	0/-18	-	844366073021
	3	120-277	Program Start	7303	BAF332PS/MV	75-73	0.88	10	0.63-0.27	0/-18	-	844366073038
			Program Start	7304	BAF332PS/MV/H	88-87	1.18	10	0.76-0.33	0/-18	-	844366073045
	1	347	Instant Start	7305	BAF232IS/347	30	1.08	10	0.09	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	28	0.89	10	0.085	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	38	1.39	10	0.112	0/-18	-	844366073076
	2	347	Instant Start	7305	BAF232IS/347	45	0.89	10	0.134	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	43	0.84	10	0.125	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	58	1.19	10	0.172	0/-18	-	844366073076
			Instant Start	7308	BAF332IS/347	49	1	10	0.146	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	46	0.93	10	0.137	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	62	1.25	10	0.184	0/-18	-	844366073106
	3	347	Instant Start	7308	BAF332IS/347	65	0.9	10	0.188	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	60	0.8	10	0.176	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	81	1.17	10	0.234	0/-18	-	844366073106
	4	347	Instant Start	7311	BAF432IS/347	82	0.87	10	0.24	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	76	0.78	10	0.225	0/-18	-	844366073120

ELECTRONIC FL BALLASTS

For 28W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F28T8 - 28W											
	1	120-277	Instant Start	7282	BAF232IS/MV	31	1.05	10	0.26-0.11	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	26	0.9	10	0.22-0.10	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	40	1.1	15	0.34-0.16	0/-18	-	844366072840
	2	120-277	Instant Start	7282	BAF232IS/MV	48	0.89	10	0.41-0.18	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	43	0.77	10	0.37-0.16	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	67	1.19	10	0.57-0.25	0/-18	-	844366072840
			Instant Start	7288	BAF332IS/MV	56	1.02	10	0.48-0.21	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	48	0.87	10	0.41-0.19	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	74	1.3	10	0.63-0.28	0/-18	-	844366072901
	3	120-277	Instant Start	7288	BAF332IS/MV	74	0.88	10	0.63-0.27	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	66	0.78	10	0.56-0.24	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	97	1.17	10	0.82-0.36	0/-18	-	844366072901
			Instant Start	7294	BAF432IS/MV	80	0.98	10	0.67-0.29	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	69-68	0.85	0	0.57-0.25	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	98-95	1.24	10	0.80-0.36	0/-18	-	844366072963

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

■ ■ ■ For 28W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F28T8 - 28W											
	4	120-277	Instant Start	7294	BAF432IS/MV	97-96	0.88	10	0.82-0.36	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	84-82	0.77	10	0.71-0.30	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	116-115	1.16	10	0.98-0.42	0/-18	-	844366072963
	2	120-277	Program Start	7300	BAF232PS/MV	52-51	0.9	10	0.44-0.19	0/-18	-	844366073007
			Program Start	7302	BAF232PS/MV/H	67	1.19	10	0.57-0.25	0/-18	-	844366073021
	3	120-277	Program Start	7303	BAF332PS/MV	72-71	0.88	10	0.60-0.26	0/-18	-	844366073038
			Program Start	7304	BAF332PS/MV/H	97	1.17	10	0.82-0.36	0/-18	-	844366073045
	1	347	Instant Start	7305	BAF232IS/347	32	1.08	10	0.098	60/16	-	844366073052
			Instant Start	7306	BAF232IS/347/L	30	0.88	10	0.09	60/16	-	844366073069
			Instant Start	7307	BAF232IS/347/H	41	1.37	10	0.123	60/16	-	844366073076
	2	347	Instant Start	7305	BAF232IS/347	50	0.89	10	0.148	60/16	-	844366073052
			Instant Start	7306	BAF232IS/347/L	46	0.83	10	0.136	60/16	-	844366073069
			Instant Start	7307	BAF232IS/347/H	66	1.18	10	0.193	60/16	-	844366073076
			Instant Start	7308	BAF332IS/347	54	0.99	10	0.16	60/16	-	844366073083
			Instant Start	7309	BAF332IS/347/L	49	0.9	10	0.147	60/16	-	844366073090
			Instant Start	7310	BAF332IS/347/H	70	1.24	10	0.209	60/16	-	844366073106
	3	347	Instant Start	7308	BAF332IS/347	71	0.86	10	0.207	60/16	-	844366073083
			Instant Start	7309	BAF332IS/347/L	65	0.79	10	0.192	60/16	-	844366073090
			Instant Start	7310	BAF332IS/347/H	92	1.15	10	0.273	60/16	-	844366073106
			Instant Start	7311	BAF432IS/347	77	0.94	10	0.226	60/16	-	844366073113
			Instant Start	7312	BAF432IS/347/L	68	0.82	10	0.201	60/16	-	844366073120
	4	347	Instant Start	7311	BAF432IS/347	93	0.87	10	0.273	60/16	-	844366073113
			Instant Start	7312	BAF432IS/347/L	84	0.77	10	0.248	60/16	-	844366073120

ELECTRONIC FL BALLASTS

For 30W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F30T8 - 30W											
	1	120-277	Instant Start	7282	BAF232IS/MV	33	1.05	10	0.28-0.12	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	28	0.9	10	0.24-0.11	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	42	1.38	10	0.25-0.16	0/-18	-	844366072840
	2	120-277	Instant Start	7282	BAF232IS/MV	51	0.89	10	0.43-0.19	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	46	0.77	10	0.39-0.17	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	72	1.19	10	0.61-0.27	0/-18	-	844366072840
			Instant Start	7288	BAF332IS/MV	59	1.02	10	0.49-0.22	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	52	0.87	10	0.44-0.20	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	78	1.3	10	0.65-0.29	0/-18	-	844366072901
	3	120-277	Instant Start	7288	BAF332IS/MV	80	0.88	10	0.68-0.28	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	71	0.78	10	0.60-0.26	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	104	1.17	10	0.88-0.38	0/-18	-	844366072901
			Instant Start	7294	BAF432IS/MV	84	0.98	10	0.71-0.31	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	75-74	0.84	10	0.62-0.27	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	105-101	1.24	10	0.88-0.37	0/-18	-	844366072963
	4	120-277	Instant Start	7294	BAF432IS/MV	105	0.88	10	0.89-0.39	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	90-88	0.77	10	0.76-0.32	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	120	1.16	10	1.01-0.44	0/-18	-	844366072963
	2	120-277	Program Start	7300	BAF232PS/MV	54-53	0.9	10	0.45-0.20	0/-18	-	844366073007
			Program Start	7302	BAF232PS/MV/H	72	1.19	10	0.61-0.27	0/-18	-	844366073021

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

■ ■ ■ For 30W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F30T8 - 30W											
	3	120-277	Program Start	7303	BAF332PS/MV	77-76	0.88	10	0.64-0.28	0/-18	-	844366073038
			Program Start	7304	BAF332PS/MV/H	104	1.17	10	0.88-0.38	0/-18	-	844366073045
	1	347	Instant Start	7305	BAF232IS/347	34	1.08	10	0.105	60/16	-	844366073052
			Instant Start	7306	BAF232IS/347/L	33	0.88	10	0.098	60/16	-	844366073069
			Instant Start	7307	BAF232IS/347/H	44	1.37	10	0.132	60/16	-	844366073076
	2	347	Instant Start	7305	BAF232IS/347	54	0.89	10	0.16	60/16	-	844366073052
			Instant Start	7306	BAF232IS/347/L	50	0.83	10	0.147	60/16	-	844366073069
			Instant Start	7307	BAF232IS/347/H	71	1.18	10	0.21	60/16	-	844366073076
			Instant Start	7308	BAF332IS/347	56	0.99	10	0.172	60/16	-	844366073083
			Instant Start	7309	BAF332IS/347/L	54	0.9	10	0.16	60/16	-	844366073090
			Instant Start	7310	BAF332IS/347/H	76	1.24	10	0.224	60/16	-	844366073106
	3	347	Instant Start	7308	BAF332IS/347	77	0.86	10	0.226	60/16	-	844366073083
			Instant Start	7309	BAF332IS/347/L	71	0.79	10	0.208	60/16	-	844366073090
			Instant Start	7310	BAF332IS/347/H	101	1.15	10	0.299	60/16	-	844366073106
			Instant Start	7311	BAF432IS/347	82	0.94	10	0.243	60/16	-	844366073113
			Instant Start	7312	BAF432IS/347/L	74	0.82	10	0.222	60/16	-	844366073120
	4	347	Instant Start	7311	BAF432IS/347	100	0.87	10	0.296	60/16	-	844366073113
			Instant Start	7312	BAF432IS/347/L	90	0.77	10	0.267	60/16	-	844366073120

ELECTRONIC FL BALLASTS

For 40W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F40T8 - 40W											
	1	120-277	Instant Start	7282	BAF232IS/MV	41	1.01	10	0.35-0.15	32/0	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	36	0.88	10	0.29-0.13	32/0	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	56-55	1.35	10	0.47-0.21	0/-18	-	844366072840
	2	120-277	Instant Start	7288	BAF332IS/MV	75-74	1.03	10	0.65-0.28	32/0	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	68	0.87	10	0.50-0.26	32/0	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	102	1.3	10	0.86-0.37	32/0	-	844366072901
	3	120-277	Instant Start	7294	BAF432IS/MV	110	0.94	10	0.93-0.39	32/0	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	98-96	0.84	10	0.82-0.35	32/0	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	143-139	1.25	10	1.22-0.51	0/-18	-	844366072963

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL