

### Dimmers Compatible with / Gradateurs Compatibles avec SO1008, 8W, 120V

Dimmer Manufacturer Fabricant de Gradateur	Part # Numéro #	Light Output / Sortie de lumière		# of Fixtures / # d'Installations	
		Min	Max	Min	Max
LUTRON®	DVCL-153	10%	90%	1	13
	SCL-153P	10%	92%	1	13
	TGCL-153PH	15%	85%	1	13
	MACL-153	10%	85%	1	12
	RRD-6CL-WH	3%	85%	1	15
	SELV300P	3%	93%	1	27
	DVELV300P	3%	95%	1	27
	MAELV-300	3%	92%	1	52
	FAELV500	3%	92%	1	45
COOPER®	DAL06P	10%	94%	1	15
	DLC03P	10%	95%	3	15
LEVITON®	6161	3%	96%	1	15
	IPL06	15%	96%	4	12
	VPI06	3%	93%	1	15
	IPE04	3%	92%	1	38
	VPE06	15%	93%	1	38
INSTEON®	2477D	10%	95%	1	15