

# JA Series



## 200 AMP SOCKET c/w Breaker

CATALOGUE #	DESCRIPTION	ENCLOSURE SIZE H X W X D	WEIGHT
<b>JA402P</b>	c/w 200 Amp breaker, 4 jaw, 120/240 VOLTS, single phase, 3 wire	30" x 10 <sup>1</sup> / <sub>4</sub> " x 5 <sup>1</sup> / <sub>4</sub> "	25 lbs.
<b>JA402PSD-LB</b>	as above, less breaker (will accomodate square D breaker only)	30" x 10 <sup>1</sup> / <sub>4</sub> " x 5 <sup>1</sup> / <sub>4</sub> "	24 lbs.
<b>JA402PSD</b>	c/w 200 amp square D breaker	30" x 10 <sup>1</sup> / <sub>4</sub> " x 5 <sup>1</sup> / <sub>4</sub> "	25 lbs.

- 200 Amp - 120/240 VOLT
- Combination meter socket & circuit breaker
- CSA enclosure 3
- Conductor range #6 - 250 MCM CU/AL
- Suitable for temporary service, farm service, trailers, recreational parks, commercial and residential locations.
- Service entrance rated

- Also available with 125 Amp breaker or 150 Amp breaker upon request
- Also available less breaker

KNOCKOUT CODE	CONDUIT SIZE
<b>G</b>	1 <sup>1</sup> / <sub>4</sub> ", 1 <sup>1</sup> / <sub>2</sub> ", 2", 2 <sup>1</sup> / <sub>2</sub> "

