

■ ■ ■ For 32W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F32T8 - 32W											
	2	120-277	Program Start	7300	BAF232PS/MV	57-56	0.88	10	0.48-0.21	0/-18	-	844366073007
			Program Start	7301	BAF232PS/MV/L	52-51	0.78	10	0.43-0.19	0/-18	-	844366073014
			Program Start	7302	BAF232PS/MV/H	72-71	1.18	10	0.60-0.26	0/-18	-	844366073021
	3	120-277	Program Start	7303	BAF332PS/MV	87-85	0.88	10	0.72-0.31	0/-18	-	844366073038
			Program Start	7304	BAF332PS/MV/H	113-110	1.18	10	0.95-0.42	0/-18	-	844366073045
	1	347	Instant Start	7305	BAF232IS/347	37	1.08	10	0.112	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	36	0.88	10	0.107	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	47	1.37	10	0.141	0/-18	-	844366073076
	2	347	Instant Start	7305	BAF232IS/347	56	0.89	10	0.17	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	51	0.83	10	0.151	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	74	1.18	10	0.222	0/-18	-	844366073076
			Instant Start	7308	BAF332IS/347	61	0.99	10	0.186	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	60	0.9	10	0.179	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	82	1.24	10	0.244	0/-18	-	844366073106
	3	347	Instant Start	7308	BAF332IS/347	81	0.86	10	0.24	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	75	0.78	10	0.225	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	107	1.15	10	0.324	0/-18	-	844366073106
			Instant Start	7311	BAF432IS/347	88	0.94	10	0.26	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	80	0.82	10	0.238	0/-18	-	844366073120
	4	347	Instant Start	7311	BAF432IS/347	108	0.87	10	0.32	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	98	0.77	10	0.296	0/-18	-	844366073120

■ ■ ■ For 25W T8 Lamps

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL

Product Information

Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F25T8 - 25W											
	4	120-277	Instant Start	7294	BAF432IS/MV	86	0.89	10	0.73-0.32	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	76-74	0.78	10	0.64-0.27	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	109	1.17	10	0.92-0.40	0/-18	-	844366072963
	2	120-277	Program Start	7300	BAF232PS/MV	50-49	1	10	0.42-0.18	0/-18	-	844366073007
			Program Start	7302	BAF232PS/MV/H	63-60	1.18	10	0.53-0.22	0/-18	-	844366073021
	3	120-277	Program Start	7303	BAF332PS/MV	75-73	0.88	10	0.63-0.27	0/-18	-	844366073038
			Program Start	7304	BAF332PS/MV/H	88-87	1.18	10	0.76-0.33	0/-18	-	844366073045
	1	347	Instant Start	7305	BAF232IS/347	30	1.08	10	0.09	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	28	0.89	10	0.085	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	38	1.39	10	0.112	0/-18	-	844366073076
	2	347	Instant Start	7305	BAF232IS/347	45	0.89	10	0.134	0/-18	-	844366073052
			Instant Start	7306	BAF232IS/347/L	43	0.84	10	0.125	0/-18	-	844366073069
			Instant Start	7307	BAF232IS/347/H	58	1.19	10	0.172	0/-18	-	844366073076
			Instant Start	7308	BAF332IS/347	49	1	10	0.146	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	46	0.93	10	0.137	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	62	1.25	10	0.184	0/-18	-	844366073106
	3	347	Instant Start	7308	BAF332IS/347	65	0.9	10	0.188	0/-18	-	844366073083
			Instant Start	7309	BAF332IS/347/L	60	0.8	10	0.176	0/-18	-	844366073090
			Instant Start	7310	BAF332IS/347/H	81	1.17	10	0.234	0/-18	-	844366073106
	4	347	Instant Start	7311	BAF432IS/347	82	0.87	10	0.24	0/-18	-	844366073113
			Instant Start	7312	BAF432IS/347/L	76	0.78	10	0.225	0/-18	-	844366073120

ELECTRONIC FL BALLASTS

For 30W T8 Lamps ■■■

Product Information												
Lamp Type	Number of lamps	Input voltage (V)	Lamp Start Method	Item#	Description	Wattage (W)	Ballast Factor	ATHD (%)	Line Current (A)	Min Start Temp (F/C)	Wiring Diagram	UPC
T8	F30T8 - 30W											
	1	120-277	Instant Start	7282	BAF232IS/MV	33	1.05	10	0.28-0.12	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	28	0.9	10	0.24-0.11	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	42	1.38	10	0.25-0.16	0/-18	-	844366072840
	2	120-277	Instant Start	7282	BAF232IS/MV	51	0.89	10	0.43-0.19	0/-18	-	844366072826
			Instant Start	7283	BAF232IS/MV/L	46	0.77	10	0.39-0.17	0/-18	-	844366072833
			Instant Start	7284	BAF232IS/MV/H	72	1.19	10	0.61-0.27	0/-18	-	844366072840
			Instant Start	7288	BAF332IS/MV	59	1.02	10	0.49-0.22	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	52	0.87	10	0.44-0.20	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	78	1.3	10	0.65-0.29	0/-18	-	844366072901
	3	120-277	Instant Start	7288	BAF332IS/MV	80	0.88	10	0.68-0.28	0/-18	-	844366072888
			Instant Start	7289	BAF332IS/MV/L	71	0.78	10	0.60-0.26	0/-18	-	844366072895
			Instant Start	7290	BAF332IS/MV/H	104	1.17	10	0.88-0.38	0/-18	-	844366072901
			Instant Start	7294	BAF432IS/MV	84	0.98	10	0.71-0.31	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	75-74	0.84	10	0.62-0.27	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	105-101	1.24	10	0.88-0.37	0/-18	-	844366072963
	4	120-277	Instant Start	7294	BAF432IS/MV	105	0.88	10	0.89-0.39	0/-18	-	844366072949
			Instant Start	7295	BAF432IS/MV/L	90-88	0.77	10	0.76-0.32	0/-18	-	844366072956
			Instant Start	7296	BAF432IS/MV/H	120	1.16	10	1.01-0.44	0/-18	-	844366072963
	2	120-277	Program Start	7300	BAF232PS/MV	54-53	0.9	10	0.45-0.20	0/-18	-	844366073007
			Program Start	7302	BAF232PS/MV/H	72	1.19	10	0.61-0.27	0/-18	-	844366073021

HID

HALOGEN

CFL

FL

BALLAST

GERMICIDAL