

**DryConn® Black/Blue***Complete list of UL 486D 600V Wire Combinations*

1 #6	1 #8 w/ 1 #12 w/ 1, 2, or 3 #14	3 #10 w/ 1 #14 or #16
2 #8	1 #8 w/ 2 #12 w/ 1 #14	3 #10 w/ 1 or 2 #18
2 or 3 #10	1 #10 w/ 2 or 3 #12	1 #12 w/ 4 or 5 #14
3, 4, or 5 #12	1 #10 w/ 3, 4, or 5 #14	2 #12 w/ 2, 3, or 4 #14
4, 5, or 6 #14	1 #10 w/ 1 #12 w/ 1, 2, 3, or 4 #14	2 #12 w/ 2, 3, or 4 #16
1 #6 w/ 1 #12	1 #10 w/ 2 #12 w/ 1, 2, or 3 #14	2 #12 w/ 3 or 4 #18
1 #6 w/ 1 or 2 #14	1 #10 w/ 3 #12 w/ 1 #14	3 #12 w/ 1, 2, 3, or 4 #14
1 #8 w/ 1#10	2 #10 w/ 1 or 2 #12	3 #12 w/ 1, 2, 3, or 4 #16
1 #8 w/ 1 or 2 #12	2 #10 w/ 1, 2, or 3 #14	3 #12 w/ 1, 2, 3, or 4 #18
1 #8 w/ 1, 2, 3, or 4 #14	2 #10 w/ 1, 2, 3, or 4 #16	4 #12 w/ 1 #14
1 #8 w/ 1 #10 w/ 1 #12	2 #10 w/ 1, 2, 3, or 4 #18	
1 #8 w/ 1 #10 w/ 1 or 2 #14	2 #10 w/ 1 #12 w/ 1 or 2 #14	